

# DY2100 | DY2200 | DY2300

## CLAMP-ON GROUND RESISTANCE AND TRUE RMS LEAKAGE CURRENT TESTER WITH USB

- 55\*32 mm jaw size for larger ground rods
- Autoranging ground resistance measurement from 0 to 1300 ohms with 0.001 ohm resolution
- True RMS AC Leakage current measurement from 0.05mA to 30A with 0.05mA Resolution
- USB connection for data downloading
- Ergonomic mold, full rubber coating and hand strap for slip proof
- Data memory 99 sets
- Verification resistor confirms accuracy of meter
- Complete with heavy duty carry case and verification resistor



| SPECIFICATION                          | RANGE                            | RESOLUTION | DY2100      | DY2200           | DY2300 |
|--|----------------------------------|------------|-------------|------------------|--------|
| Earth Resistance                       | 0.01Ω~0.099Ω±(1%±0.01Ω )         | 0.001Ω     | ●           | ●                | ●      |
|  | 0.10Ω~0.99Ω±(1%+0.01Ω )          | 0.01Ω      | ●           | ●                | ●      |
|  | 1.0Ω~49.9Ω±(1.5%+0.1Ω )          | 0.1Ω       | ●           | ●                | ●      |
|  | 50.0Ω~99.5Ω±(2%+0.5Ω )           | 0.5Ω       | ●           | ●                | ●      |
|  | 100Ω~199Ω±(3%+1Ω )               | 1Ω         | ●           | ●                | ●      |
|  | 200Ω~395Ω±(6%+5Ω )               | 5Ω         | ●           | ●                | ●      |
|  | 400Ω~590Ω±(10%+10Ω )             | 10Ω        | ●           | ●                | ●      |
|  | 600Ω~1000Ω±(20%+20Ω )            | 20Ω        | ●           | ●                | ●      |
| Min. Resolution                        |                                  | 0.001Ω     | ●           | ●                | ●      |
| Configurable alarm value of resistance | 0~199Ω                           |            | ●           | ●                | ●      |
| Leakage Current                        | 0 ~ 80mA±(2.5%+1mA)              | 50μA       | ●           | ●                | ●      |
|  | 80mA ~ 650mA±(2.5%+2mA)          | 0.5mA      | ●           | ●                | ●      |
|  | 650mA ~ 4A±(2.5%+10mA)           | 5mA        | ●           | ●                | ●      |
|  | 4A ~ 30A±(2.5%+20mA)             | 10mA       | ●           | ●                | ●      |
| Min. Resolution                        |                                  | 50μA       | ●           | ●                | ●      |
| Configurable alarm value of current    | 0~499mA                          |            | ●           | ●                | ●      |
| Measurement of Leakage Current         |                                  |            | 45~65Hz RMS | 45~65Hz True RMS |        |
| Memory                                 | 99 sets                          |            | ●           | ●                | ●      |
| USB interface                          |                                  |            | ●           | ●                | ●      |
| Conductor Size                         | Φ55mm*32mm                       |            | ●           | ●                | ●      |
| Working Temperature                    | -10° C ~ 55° C                   |            | ●           | ●                | ●      |
| Working Humidity                       | 10%~80%                          |            | ●           | ●                | ●      |
| LCD Size                               | 28*46mm                          |            | ●           | ●                | ●      |
| Power Supply                           | AA 1.5V*4                        |            | ●           | ●                | ●      |
| Dimension                              | 285*90*60mm                      |            | ●           | ●                | ●      |
| Weight                                 | approx. 1250g (battery included) |            | ●           | ●                | ●      |

### STANDARD ACCESSORIES

Verification Resistor



Carry case

